

## KBHD Dual Blower Arr. 1 w/Mixing Box


JOB NAME \_\_\_\_\_\_
ENGINEER \_\_\_\_\_
CONTRACTOR \_\_\_\_\_
TAG

DUAL DIRECT DRIVE BLOWER COIL UNIT DISHARGE ARGT. 1 W/ MIXING BOX


## **SUBMITTAL SHEET**

## NOTES:

- All dimensions are in Inches [millimeters]. All dimensions are ±1/4" [6mm]. Metric values are soft conversion.
- Right hand unit shown, Left hand unit opposite. Motor/ drive location may be specified Left or Right Hand. Standard control enclosure location matches motor/ drive position.
- Provide sufficient clearance to permit access to controls and comply with applicable codes and ordinances.
- 4. See drawing BCS-KBOD-ACFR0 for filter rack details.
- Base rail is optional on the base unit. See drawing BCS-KBOD-ACEB0. Base rails must be used with mixing box.
- 6. See coil connection detail drawings for coil connection sizes and locations.



**TOP VIEW** 



DIMENSIONS												
UNIT SIZE	FAN SIZE	L	w	Н	A	В	С	D	E	F	G	J
30	<b>10 x 8</b> [254 x 203]	<b>67</b> [1702]	<b>59</b> [1499]	<b>30</b> [762]	<b>46</b> [1168]	<b>21</b> [533]	<b>12</b> [305]	<b>45</b> [1143]	<b>7</b> [178]	<b>18</b> [457]	<b>36 1/2</b> [927]	<b>11 1/4</b> [286]
40	<b>10 x 8</b> [254 x 203]	<b>70</b> [1778]	<b>68</b> [1727]	<b>30</b> [762]	<b>46</b> [1168]	<b>24</b> [610]	<b>15</b> [381]	<b>48</b> [1219]	<b>10</b> [254]	<b>18</b> [457]	<b>36 1/2</b> [927]	<b>15 3/4</b> [400]

Revision Date: NEW Form: BCS-KBHD-A1MB1 Replaces: XXXXXXXXX SH
----------------------------------------------------------------